



- HOME
- PRODUCTS ▶
- FEATURES
- TUTORIAL
- PHOTO GALLERY
- UPCOMING EVENTS
- REQUEST INFO
- DISTRIBUTOR LIST
- CONTACT US
- REPAIR FORM

[<< Previous](#)

[Next >>](#)



StartPac Portable Power Supply Model 53025/12V



[DOWNLOAD BROCHURE](#)

[FINANCING AVAILABLE](#)

[Email this page](#)

Model 53025/12V

Specifications:

- AC INPUT: 90 to 240 VAC, 7 amps
- DC OUTPUT: 25 amps @ 14.2 Volts
- 9 Lbs./4.08 kilos complete
- 14" long, 5.25" wide, 5.5" high
- Continuous duty fan cooled
- Over current protection
- Over voltage protection
- Over temperature protection

Do not cover or enclose this Start Pac® when using, as this will inhibit airflow needed for cooling purposes.

Use a minimum of 12# wire size for the AC extension cord.

This Start Pac® Portable Power Supply is a 12 Volt output unit.

The Start Pac® Portable Power Supply model 53025/12 is designed to power up 12 Volt aircraft systems. The voltage output is set to 14.2 Volts to simulate the same voltage as when the aircraft is running under power. Maximum amperage output is 50 amps which is adequate for most light aircraft. If overloaded, the 53025/12 will trip off and reset itself after a short period of time. This unit is ideal for powering up new and old aircraft with glass cockpits.

When utilizing the 53025/12, the entire aircraft electrical system can be powered up for GPS programming and electrical maintenance. Thus the on board aircraft battery can be saved for starting.

Do not use for starting as starter motors require far more amperage than is available from the StartPac® Portable Power Supply. This unit will operate on 110/220Volt AC input.

Not for battery charging.

Made in the USA.

- [Home](#) | [Features](#) | [Pictures](#) | [24 V vs. 28V Tutorial](#)
[Model 1324-1QC](#) | [Model 1628QC](#) | [Model 2300QC](#) | [Model Li2000QC](#) | [Model Li2600QC](#)
[Model Li2800QC](#) | [Model Li2800 Twin Pac](#) | [Earth Gear 2300QC](#) | [Model 6028QC](#)
[Model 3324](#) | [Model 3324-1](#) | [Model 3324-2](#) | [Model 3324RR Locomotive](#) | [Model 3328](#) | [Model 3328 Special](#)
[Model 53025/12V](#) | [Model 53025/24V](#) | [Model 53050](#) | [Model 53105](#)
[Self-Propelled Gasoline-Electric Hi-Brd™](#) | [Self-Propelled Diesel-Electric Hi-Brd™](#) | [Start Pac Trolley](#)

Rotorcraft Enterprises

Shipping and Mailing address:

4060 Schiff Drive | Las Vegas, NV. 89103

Tel: (702) 982-7089 or (702) 405-7904 | Fax: (702) 982-6925

jim@startpac.com or judith@startpac.com or eve@startpac.com

Web Site Design by [eDesigners.net](#). © Rotorcraft Enterprises 1998-2008. All Rights Reserved.