



Not for engine starting
Not for battery charging

The START PAC® model 53400 – 24/28V is the most powerful power supply. It has been designed to power up 24 Volt aircraft systems and will continuously deliver up to full 400 amp DC output. The voltage output is set to 28 Volts to simulate the same voltage as when the aircraft is running under power.

This START PAC® unit has been specifically designed for maintenance and to power up various functions such as inverters, avionics, GPS programming, on-board air conditioning and any other on-board system. Using this START PAC® power supply means that the operator can bypass the aircraft battery thus preserving it from unnecessary wear. The on-board aircraft battery can be conserved for starting only. The environmentally responsible, low VOC powder coating protects the unit from wear, tear and poor weather conditions.



Proprietary
Copyright © 2020 START PAC



SPECIFICATIONS	
Maximum Continuous Current output	400 A
DC voltage output	28 VDC
AC voltage input	180 - 240 VAC
AC current input at maximum DC power output	53 A @220VAC
Phase	1
Forced air-cooling	YES
Over current protection	YES
Over voltage protection	YES
Over temperature protection	YES
Complete weight	60lbs / 27kg
Dimensions Length x Width x Height	50" x 23" x 23" 127 x 58 x 58 cm

PRODUCT FEATURES

- Most powerful mobile aircraft power supply
- No duty cycle, clean continuous power
- Voltage output 28 Volts and 400 Amps maximum amperage output
- Resistant aluminum case with environment friendly, low VOC durable powder coat finish, easy to handle, built for heavy duty usage
- 10'/3m aircraft removeable cable
- If overloaded, the unit will trip off and reset itself after a short period of time



Proprietary
Copyright © 2020 START PAC

